arXiv:0706.0301v1 [hep-th] 3 Jun 2007

Generalized Electromagnetic fields of Dyons in Inhomogenous Media

P. S. Bisht, O. P. S. Negi and Jivan Singh

February 1, 2008

Department of Physics
Kumaun University
Soban Singh Jeena Campus
Almora-263601 (Uttarakhand)
INDIA

Email:- ps_bisht123@rediffmail.com
ops_negi@yahoo.co.in
jivan@indiatimes.com

Abstract

Reformulation of the generalized electromagnetic fields of dyons has been dicussed in inhomogenous media and corresponding quaternionic equations are derived in compact, simple and unique manner. We have also discussed the monochromatic fields of generalized electromagnetic fields of dyons in slowly changing media in a consistent manner.

In the series of papers we have discussed the Maxwell's-Dirac equation in the homogenous (isotropic) medium and its solutions [1], quaternionic form of the generlaized fields of dyons in homogenous (isotropic) medium and other quantum equations [2], time-harmonic form of generalized fields of dyons in homogenous (isotropic) medium [3] and in the presence of source the time-dependent Maxwell's -Dirac equation have been developed in chiral media and the solution for the problem are obtained in unique and consistent manner [4]. In this paper we have reformulated the generalized electromagnetic fields of dyons in inhomogenous media and corresponding quaternionic equations are derived in compact, simple and unique manner. Finally we have also discussed the monochromatic fields of generalized electromagnetic fields of dyons in slowly changing media in a consistent manner.

Postulating the existence of magnetic monopoles[5], let us write the Generalized Dirac Maxwell (GDM) field equations in isotropic (homogenous) medium in the following manner [1] in terms of natural units $c = \hbar = 1$;

$$\begin{aligned}
\overrightarrow{\nabla}.\overrightarrow{D} &= \rho_e \\
\overrightarrow{\nabla}.\overrightarrow{B} &= \mu\rho_m \\
\overrightarrow{\nabla} \times \overrightarrow{E} &= -\frac{\partial \overrightarrow{B}}{\partial t} - \frac{\overrightarrow{j_m}}{\epsilon} \\
\overrightarrow{\nabla} \times \overrightarrow{H} &= \frac{\partial \overrightarrow{D}}{\partial t} + \overrightarrow{j_e} \qquad (1)
\end{aligned}$$

Where ρ_e and ρ_m are respectively the electric and magnetic charge densities, $\overrightarrow{j_e}$ and $\overrightarrow{j_m}$ are the electric and magnetic current densities, $\overrightarrow{D}$ is electric displacement vector, $\overrightarrow{E}$ is the electric field, $\overrightarrow{B}$ is magnetic induction vector and $\overrightarrow{H}$ is magnetic field. ε and μ are respectively the permiability and permitivity of the media.

Assuming that ϵ and μ are the function of coordinates [6] such as

$$\epsilon = \epsilon(x)$$

and

$$\mu = \mu(x). \qquad (2)$$

The Maxwell's equations are thus considered together with the relation given by (2) may then be written accordingly in inhomogeneous media describing relations among the induction and the field vectors. Let us now define $\overrightarrow{D}$ and $\overrightarrow{B}$ as,

$$\overrightarrow{D} = \overrightarrow{D}\,(\overrightarrow{E},\overrightarrow{H})$$

$$\overrightarrow{B} = \overrightarrow{B}\,(\overrightarrow{E},\overrightarrow{H}) \tag{3}$$

and

$$\overrightarrow{D} = \epsilon_0\epsilon_r\overrightarrow{E}$$

$$\overrightarrow{B} = \mu_0\mu_r\overrightarrow{H}. \tag{4}$$

Using the relation (3), we may write the generalized Dirac-Maxwell (GDM) equations (1) for the isotropic inhomogenous medium for dyons as

$$\overrightarrow{\nabla}.(\epsilon\overrightarrow{E}) = \rho_e$$

$$\overrightarrow{\nabla}.(\overrightarrow{B} \quad) = \mu\rho_m$$

$$\overrightarrow{\nabla}\times\overrightarrow{E} = -\frac{\partial\overrightarrow{B}}{\partial t} - \frac{\overrightarrow{j_m}}{\epsilon}$$

$$\overrightarrow{\nabla}\times\overrightarrow{B} = \frac{1}{v^2}\frac{\partial\overrightarrow{E}}{\partial t} + \mu\overrightarrow{j_e}. \tag{5}$$

The first and second differential equations of GDM equations (5) can be written as follows [7] ,

$$div\overrightarrow{E} \quad + < \tfrac{grad\epsilon}{\epsilon}, \quad \overrightarrow{E} >= \frac{\rho_e}{\epsilon} \tag{6}$$

and

$$div\overrightarrow{B} \quad + < \tfrac{grad\mu}{\mu}, \quad \overrightarrow{B} >= \mu\rho_m. \tag{7}$$

Combining equations (6) and (7) with the third and fourth equation of (5), we obtain the following form of generalized Dirac-Maxwell (GDM) equations i.e.

$$div\overrightarrow{E} \quad =< \tfrac{grad\epsilon}{\epsilon}, \quad \overrightarrow{E} > -\frac{\partial\overrightarrow{B}}{\partial t} - \frac{\overrightarrow{j_m}}{\epsilon} - \frac{\rho_e}{\epsilon} \tag{8}$$

and

$$div\overrightarrow{B} \quad =< \tfrac{grad\mu}{\mu}, \quad \overrightarrow{B} > \frac{1}{v^2}\frac{\partial\overrightarrow{E}}{\partial t} - \mu\overrightarrow{j_e} - \mu\rho_m. \tag{9}$$

Let us take the scalar products of two vectors $\overrightarrow{p}$ and $\overrightarrow{q}$ as,

$$< \overrightarrow{p}, \overrightarrow{q} > \quad = \quad -\frac{1}{2}(\overrightarrow{p}M + M\overrightarrow{p})\overrightarrow{q}. \tag{10}$$

Using this equation (10), we get the following pair of equations from equations (8) and (9) as

$$(D + \frac{1}{2}\frac{grad\epsilon}{\epsilon})\overrightarrow{E} \quad = -\tfrac{1}{2}M^{\frac{grad\epsilon}{\epsilon}}\overrightarrow{E} - \tfrac{\partial\overrightarrow{B}}{\partial t} - \tfrac{\overrightarrow{j_m}}{\epsilon} - \quad \frac{\rho_e}{\epsilon} \tag{11}$$

and

$$(D + \frac{1}{2}\frac{grad\mu}{\mu})\overrightarrow{B} \quad = -\tfrac{1}{2}M^{\frac{grad\mu}{\mu}}\overrightarrow{B} - \quad \frac{1}{v^2}\frac{\partial\overrightarrow{E}}{\partial t} - \mu\overrightarrow{j_e} - \mu\rho_m. \tag{12}$$

where we have used the following subsidiary condition

$$\frac{1}{2}\frac{grad\epsilon}{\epsilon} = \frac{grad\sqrt{\epsilon}}{\sqrt{\epsilon}}. \tag{13}$$

Then using the condition given by Kravehenko [7], we may write equations (11) and (12) as follows,

$$\frac{1}{\sqrt{\epsilon}}D(\sqrt{\epsilon}.\overrightarrow{E}) + \overrightarrow{E}.\overrightarrow{\epsilon} = = -\frac{\partial \overrightarrow{B}}{\partial t} - \frac{\overrightarrow{j_m}}{\epsilon} - \frac{\rho_e}{\epsilon} \tag{14}$$

$$\frac{1}{\sqrt{\mu}}D(\sqrt{\mu}.\overrightarrow{B}) + \overrightarrow{B}.\overrightarrow{\mu} = \frac{1}{v^2}\frac{\partial \overrightarrow{E}}{\partial t} - \mu\overrightarrow{j_e} - \mu\rho_m \tag{15}$$

where

$$\overrightarrow{\epsilon} = \frac{grad\sqrt{\epsilon}}{\sqrt{\epsilon}};$$

and

$$\overrightarrow{\mu} = \frac{grad\sqrt{\mu}}{\sqrt{\mu}}.$$

Rearranging the equations (14) and (15), we get the following new set of equations i.e.

$$(D + M^{\overrightarrow{\epsilon}})\overrightarrow{E} = -\frac{\partial \overrightarrow{B}}{\partial t} - \frac{\overrightarrow{j_m}}{\epsilon} - \frac{\rho_e}{\epsilon} \tag{16}$$

$$(D + M^{\overrightarrow{\mu}})\overrightarrow{B} = \frac{1}{v^2}\frac{\partial \overrightarrow{E}}{\partial t} - \mu\overrightarrow{j_e} - \mu\rho_m. \tag{17}$$

In order to write the quaternionic equation for electromagnetic fields in inhomogeneous medium, let us start with the following representations for the quaternionic differential operator [2],

$$\boxdot = \left(\frac{i}{v}\partial_t + D\right) \tag{18}$$

and its conjugate as

$$\overline{\boxdot} = \left(-\frac{i}{v}\partial_t - D\right) \tag{19}$$

where $v = \frac{1}{\sqrt{\epsilon\mu}}$ is the speed of the electromagnetic wave in the medium. We define the complex vector field $\overrightarrow{\psi}$ associated with the generalized electromagnetic fields of dyons as [2],

$$\overrightarrow{\psi} = \overrightarrow{E} - i\, v\, \overrightarrow{B}. \tag{20}$$

Accordingly, we can express the quantum equations associated with the generalized four-current, electric and magnetic fields of dyons in quaternionic form as,

$$j = -i\rho v + j_1 e_1 + j_2 e_2 + j_3 e_3 \tag{21}$$

$$E = E_1 e_1 + E_2 e_2 + E_3 e_3 \tag{22}$$

$$B = B_1 e_1 + B_2 e_2 + B_3 e_3 \tag{23}$$

$$D = D_1 e_1 + D_2 e_2 + D_3 e_3 \tag{24}$$

where e_0, e_1, e_2, e_3 are the quaternion units and satisfy the following commutation rules,

$$e_i e_j = -\delta_{ij} + \varepsilon_{ijk} e_k \tag{25}$$

where δ_{ij} is Kronecker delta and ε_{ijk} is the Levi-Civita three index symbol.

Operating equation (19) to equation (20) and using equations (16) and (25), we get

$$\overline{\boxdot}\psi = (M^{\overrightarrow{\epsilon}}\overrightarrow{E} + ivM^{\overrightarrow{\mu}}\overrightarrow{B}) + iv\mu(-iv\overline{\rho} + j) \tag{26}$$

where j is the generalized current density of dyon and given by,

$$j = j_e - i\,v\,j_m \tag{27}$$

and $\overline{\rho}$ is the conjugate of the generalized charge density of dyon and defined as,

$$\rho = \rho_e - i\frac{\rho_m}{v}. \tag{28}$$

From equation (20), we get the following relations,

$$\overrightarrow{E} = \frac{1}{2}(\psi + \psi*) \tag{29}$$

and

$$\overrightarrow{B} = \frac{1}{2iv}(\psi * - \psi) \tag{30}$$

where $\psi*$ is the complex conjugate of ψ .Taking the first part of the right hand side of equation (26), we get

$$M^{\overrightarrow{\epsilon}}\overrightarrow{E} + ivM^{\overrightarrow{\mu}}\overrightarrow{B} = \frac{1}{2}(M^{(\overrightarrow{\epsilon}-\overrightarrow{\mu})}\psi + M^{(\overrightarrow{\epsilon}+\overrightarrow{\mu})}\psi*). \tag{31}$$

We may now introduce the notation

$$\vec{\epsilon} + \vec{\mu} \quad = \quad -\frac{grad v}{v} \tag{32}$$

and

$$\vec{\epsilon} - \vec{\mu} \quad = \quad -\frac{grad W}{W} \tag{33}$$

where W is the intrinsic wave impedance of the medium. The $\vec{v}$ and $\vec{W}$ are also expressed as

$$\vec{v}: \quad = \quad \frac{grad\sqrt{v}}{\sqrt{v}} \tag{34}$$

and

$$\vec{W}: \quad = \quad \frac{grad\sqrt{W}}{\sqrt{W}}. \tag{35}$$

Thus equation (31) reduces to

$$M^{\vec{\epsilon}}\vec{E} + i\,v\,M^{\vec{\mu}}\,\vec{B} \quad = \quad -(M^{\vec{v}}\vec{\psi} * + M^{\vec{W}}\vec{\psi}) \tag{36}$$

As such, from equation (26), we obtain the generalized Dirac Maxwell (GDM) equation of dyons for an inhomogenous medium as under,

$$\boxdot\psi + \quad (M^{\vec{v}}\vec{\psi} * + M^{\vec{W}}\vec{\psi} \quad) = iv\mu(-iv\overline{\rho} + j) = i\,v\,\mu\,\overline{j}. \tag{37}$$

So, the equation (37) is completely analogous to the generalized Dirac Maxwell (GDM) equation of dyons given by equation (5) and represents the quaternionoc form of Maxwell's equation for dyons in inhomogenous medium.

Let us define a time harmonic electromagnetic field as [3],

$$\vec{E}(x,t) \quad = \quad Re(\vec{E}(x)e^{-i\omega t}) \tag{38}$$

and

$$\overrightarrow{B}(x,t) = Re(\overrightarrow{B}(x)e^{-i\omega t}). \tag{39}$$

Here ω is the frequency of oscillation. We may now assume that the sources are also considered as time-harmonic and accordingly we may write the charge and current source densities of dyons as

$$\rho(x,t) = Re(\rho(x)e^{-i\omega t}) \tag{40}$$

and

$$\overrightarrow{j}(x,t) = Re(\overrightarrow{j}(x)e^{-i\omega t}). \tag{41}$$

Hence for the case when electromagnetic field is considered to be monochromatic, we may obtain the following sets of quaternionic equations for generalized fields of dyons on substituting equations (38,39,40,41) into the equations (16) and (17) i.e.

$$D_{\overrightarrow{\epsilon}}\overrightarrow{E} = i\omega\overrightarrow{B} - \frac{\rho_e}{\epsilon} - \frac{\overrightarrow{j_m}}{\epsilon} = i\alpha v\overrightarrow{B} - \frac{\rho_e}{\epsilon} - \frac{\overrightarrow{j_m}}{\epsilon} \tag{42}$$

and

$$D_{\overrightarrow{\mu}}\overrightarrow{B} = -\frac{i\omega}{v^2}\overrightarrow{E} - \mu\rho_m + \mu\overrightarrow{j_e} = -\frac{i\alpha}{v}\overrightarrow{E} - \mu\rho_m + \mu\overrightarrow{j_e}. \tag{43}$$

In equation (42) and (43) the quantity $\alpha = \frac{\omega}{v}$ is described as the wave number. Hence for sourceless condition, the equation (42) and (43) are reduced to

$$D_{\overrightarrow{\epsilon}}\overrightarrow{E} = i\alpha v\overrightarrow{B} \tag{44}$$

and

$$D_{\overrightarrow{\mu}}\overrightarrow{B} \quad = \quad -\frac{i\alpha}{v}\overrightarrow{E}. \tag{45}$$

The medium is said to be slowly changing when its properties change appreciably over distances much greater than the wavelength [8]. Generally that is associated with the possibilty of reducing the generalized Dirac-Maxwell (GDM) equations of dyons (44) and (45) to the following forms of Helmholtz equations,

$$(\triangle + \alpha^2)\overrightarrow{E} \quad = \quad 0 \tag{46}$$

and

$$(\triangle + \alpha^2)\overrightarrow{B} \quad = \quad 0 \tag{47}$$

where

$$\triangle + \alpha^2 \quad = -(D+\alpha)(D-\alpha) = \quad -D_{\alpha}D_{-\alpha}. \tag{48}$$

For checking the reduction , we consider that $|\overrightarrow{\epsilon}|$ and $|\overrightarrow{\mu}|$ are very small and the terms containing the vectors $\overrightarrow{\epsilon}$ and $\overrightarrow{\mu}$ are supposed to be negligible. Then equations (44) and (45) are reduced to the following simple and compact quaternionic forms i.e.

$$D\overrightarrow{E} \quad = \quad i\alpha v\overrightarrow{B} \tag{49}$$

and

$$D\overrightarrow{B} \quad = \quad -\frac{i\alpha}{v}\overrightarrow{E} \tag{50}$$

These equations can be diagonalized. Hence we may obtain the following compact quaternionic equations for the functions ψ and $\psi*$ of dyons i.e.

$$D_{-\alpha}\overrightarrow{\psi} \quad = \quad 0 \tag{51}$$

and

$$D_{\alpha}\overrightarrow{\psi}* \quad = \quad 0. \tag{52}$$

These equations are completely equivalent to the Maxwell's system used for the case of particles carrying electric and magnetic charges (dyons) and thus represent the Generalized Dirac Maxwell (GDM) equations for inhomogeneous media in quaternionic formulation. The foregoing analysis is simple, compact and unique one in the sense it is manifestly covariant under homogeneous Lorentz transformations as well as it remains invariant under the usual quaternion transformations. It reduces to the quaternion equations for electromagnetic fields in inhomogeneous medium described by Kravchenko [6] in the absence of magnetic monopole on dyons. Accordingly it can be discussed for the case of particles carrying pure magnetic monopole in the absence of electric charge on dyons.

References

[1] Jivan Singh, P. S. Bisht and O. P. S. Negi, "Generalized electromagnetic fields of dyons in Isotropic medium", arXiv:hep-th/0611208.

[2] Jivan Singh, P. S. Bisht and O. P. S. Negi, "Quaternion Analysis for generalized electromagnetic fields of dyons in Isotropic medium", arXiv:hep-th/0703083.

[3] Jivan Singh, P. S. Bisht and O. P. S. Negi, "Quaternion Analyticity of Time-Harmonic Dyon Field Equations", arXiv:hep-th/0703107.

[4] Jivan Singh, P. S. Bisht and O. P. S. Negi, "Generalized Electromagnetic fields in Chiral Media",arXiv:hep-th/0703109.

[5] P. A. M. Dirac, Proc. Royal Soc. London Sec A, **133** (1931), 60.

[6] V. V. Kravchenko and Marco P. Ramfrez, " A quaternionic reformulation of Maxwell's equations for inhomogeneous media", Proceedings

of the IEEE Guanajuato Mexico Section 1st International Workshop in Mathematical modelling of Physical processes inhomogeneous media, March 20-2, 2001 Guanajuato Mexico, 59-61. V.V. Kravchenko, and M.V. Shapiro, 'Integral Representations for Spatial Models of Mathematical Physics',Harlow:Addison Wesley Longman Ltd. (1996).

[7] V. V. Kravchenko, "Applied Quaternionic Analysis, Research and Exposition in Mathematics", Heldermann Press, Germany, 28 (2003) and reference therein; "Quaternionic equation for electromagnetic fields in inhomogeneous media", math-ph/0202010; Sergei M. Grudsky, Kira V. Khmelnytskayam and V.V. Kravchenko, "On a quaternionic Maxwell equation for the time-dependent electromagnetic field in a chiral media", math-ph/0309062.

[8] V. M. Babich and V. S. Buldyrev, 'Short Wavelength Diffraction Theory Asymptotic Methods', Springer, Berlin, 1991.